MURR ELEKTRONIK
stay connected

## EUROCARD HOLDER


SKT 32 F, Z+B


Screw terminals
32-pole F (EN 60603)
Row b, z
The D2 size is for a card without a front plate.
To insert the card first press down the 2 yellow buttons. Then slide the Eurocard into the guide slots pushing until fully engaged. The card is now locked into position. It can be removed by pressing down on the 2 yellow buttons.

### Link to Product

**Illustration**






Product may differ from Image

**Commercial data**

| | |
|---|---|
| ECLASS-6.0 | 27260710 |
| ECLASS-6.1 | 27260704 |
| ECLASS-7.0 | 27440402 |
| ECLASS-8.0 | 27440402 |

The information in this Product-PDF has been compiled with the utmost care.
Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 2024-03-28

| | |
|---|---|
| ECLASS-9.0 | 27440402 |
| ECLASS-10.1 | 27440402 |
| ECLASS-11.1 | 27460201 |
| ECLASS-12.0 | 27460201 |
| ETIM-5.0 | EC002780 |
| customs tariff number | 85366990 |
| GTIN | 4048879042017 |
| Packaging unit | 1 |
| **Electrical data \| Supply** | |
| Operating voltage AC | 250 V |
| Operating current max. | 4 A |
| **Installation** | |
| Connection cross-section solid max. | 4 mm² |
| **Installation \| Pin assignment** | |
| No. of poles | 32 |
| **Device protection \| Electrical** | |
| Overvoltage category (EN 60664-1) | I |
| **Device protection \| Media** | |
| Flame resistance | flame retardant |
| **Mechanical data** | |
| Type of socket connector | F (EN 60603) |
| **Mechanical data \| Material data** | |
| Material housing | Plastic |
| **Mechanical data \| Mounting data** | |
| Mounting method | screwed, geschnappt |
| Suitable for mounting type | horizontal, vertical, mounting rail, (EN 60715) |
| Height | 112 mm |
| Width | 45 mm |
| Depth | 145 mm |

The information in this Product-PDF has been compiled with the utmost care.
Liability for the correctness completeness and topicality of the information is restricted to gross negligence. Version: 2024-03-28